


## Electronic Power Supply & Keypad

### MP-MPS-NO/C

Electronic Power Supply

電子變壓器



**SPECIFICATIONS :**

Dimension : 175L x 80W x 65Dmm  
 Input voltage : 220VAC, 50HZ  
 Output voltage : 12VDC, 3A  
 Time : 0~30sec.  
 Built-in fuse for overload and short circuit protection


**規格:**

外觀尺寸: 175L x 80W x 65Dmm  
 輸入電壓: 220VAC, 50HZ  
 輸出功率: 直流輸出標準12VDC、3A  
 延時功能: 0-30秒  
 內置保險管過載及短路保護

### MP-MPSE-NO/C

Electronic Power Supply

電子變壓器



**SPECIFICATIONS :**

Dimension : 147L x 105W x 65Dmm  
 Input voltage : 220VAC, 50HZ  
 Output voltage : 12VDC, 3A  
 Time : 0~30sec.  
 Built-in fuse for overload and short circuit protection  
 Exposed contact points for easy installation

**規格:**

外觀尺寸: 147L x 105W x 65Dmm  
 輸入電壓: 220VAC, 50HZ  
 輸出功率: 直流輸出標準12VDC、3A  
 延時功能: 0-30秒  
 內置保險管過載及短路保護  
 外露接口方便施工

### MP-9510 / MP-9810

Digital Access Keypad

門禁密碼盤



MP-9510



MP-9810

**SPECIFICATIONS :**

Dimension :  
 MP-9510 : 117W x 48H x 74Dmm  
 MP-9810 : 117W x 117H x 21Dmm  
 Voltage : 12VDC  
 Current : 90mA

**規格:**

外觀尺寸 :  
 MP-9510 : 117W x 48H x 74Dmm  
 MP-9810 : 117W x 117H x 21Dmm  
 輸入電壓 : 12VDC  
 輸入電流 : 90mA